

Electromechanical noise in a diffusive conductor

A. V. Shytov¹, L. S. Levitov², and C. W. J. Beenakker³

¹*Institute for Theoretical Physics, University of California, Santa Barbara, CA 93106-4030*

²*Department of Physics, Center for Materials Science & Engineering,
Massachusetts Institute of Technology, Cambridge, MA 02139*

³*Instituut-Lorentz, Universiteit Leiden, P.O. Box 9506, 2300 RA Leiden, The Netherlands*
(29 October 2001)

Electrons moving in a conductor can transfer momentum to the lattice via collisions with impurities and boundaries, giving rise to a fluctuating mechanical stress tensor. The root-mean-squared momentum transfer per scattering event in a disordered metal (of dimension L greater than the mean free path l and screening length ξ) is found to be reduced below the Fermi momentum by a factor of order l/L for shear fluctuations and $(\xi/L)^2$ for pressure fluctuations. The excitation of an elastic bending mode by the shear fluctuations is estimated to fall within current experimental sensitivity for a nanomechanical oscillator.

PACS numbers: 85.85.+j, 73.23.-b, 73.50.Td, 77.65.-j

Impressive advances in the fabrication of miniature mechanical oscillators provide new opportunities for research in mesoscopic physics [1,2]. The coupling of electrical and mechanical degrees of freedom is of particular interest. We mention the observation of thermal vibration [3] and acoustoelectric effects [4] in carbon nanotubes, the coupling of the centre-of-mass motion of C_{60} molecules and single-electron hopping [5], and also theoretical work [6] on the coupling between a tunneling electrical current and a localized phonon mode.

The present paper was motivated by a question posed to us by M. Roukes: Electrons in a metal collide with impurities and thereby exert a fluctuating force on the lattice. In equilibrium this electromechanical force can not be distinguished from other sources of thermal noise. Might it be measurable out of equilibrium by driving a current through a nanoscale oscillator? To address this question one has to consider a delicate balance of forces.

We will provide both a general theory and a specific application to the electromechanical excitation of a bending mode in the geometry of Fig. 1: A thin elastic beam connecting two massive Ohmic contacts. The beam could be a conductor or an insulator covered with a metal (*e.g.* a metallized suspended silicon beam [7]). We calculate the excess noise in the bending mode that arises in the presence of a dc voltage V and conclude that it should be observable on the background of the thermal noise.

Let us first discuss the order of magnitude. The noise at low temperatures is due to the $\mathcal{N}eV/E_F$ “noisy” electrons within a range eV of the Fermi energy E_F (with \mathcal{N} the total electron number in the metal). Each electron transfers to the lattice a typical momentum $\Delta p \simeq p_F$ in a scattering time τ . The mean squared momentum transfer in a time t for *uncorrelated* increments Δp would be

$$(\mathcal{N}eV/E_F)(\Delta p)^2(t/\tau) \simeq \mathcal{N}m^*eV(t/\tau) \equiv \mathcal{P}_{\max}t, \quad (1)$$

with m^* the electron effective mass.

We find that \mathcal{P}_{\max} overestimates the fluctuations in the transverse force. The actual noise power is of order

$\mathcal{P} \simeq (l/L)^2 \mathcal{P}_{\max}$, with L the length of the beam and l the mean free path in the metal. The reduction is due to the fact that subsequent momentum transfers are strongly correlated, basically because an electron being scattered back and forth alternately transfers positive and negative momentum to the lattice. The factor $(l/L)^2$ reduces the noise substantially, but we estimate that it should be observable in an oscillator with a $10^{-16} \text{ N}/\sqrt{\text{Hz}}$ sensitivity [2,7].




FIG. 1. Sketch of an elastic beam clamped at both ends to a contact and covered by a metal layer. A current flowing through the metal excites a bending mode $u(x)$ of the beam.

We combine two independently developed theoretical frameworks: The dynamic theory of elasticity [8,9] and the kinetic theory of fluctuations [10]. We start from the Boltzmann-Langevin equation of Kogan and Shulman. This is a kinetic equation with a fluctuating source $\delta J(\mathbf{r}, \mathbf{p}, t)$, that describes fluctuations in time of the distribution function $n(\mathbf{r}, \mathbf{p}, t)$,

$$(\partial_t + \mathbf{v} \cdot \nabla_{\mathbf{r}} + e\mathbf{E} \cdot \nabla_{\mathbf{p}} + \mathcal{S})n = \delta J. \quad (2)$$

Here $\mathbf{p} = m^*\mathbf{v}$ is the quasimomentum and $\mathbf{E}(\mathbf{r}, t)$ is the electric field. The collision integral \mathcal{S} for elastic scattering on impurities (with rate W) is given by

$$Sn(\mathbf{p}) = \langle W(\hat{\mathbf{p}} \cdot \hat{\mathbf{p}}') [n(\mathbf{p}) - n(\mathbf{p}')] \rangle_{\hat{\mathbf{p}}}. \quad (3)$$

The angular brackets indicate an average over the direction $\hat{\mathbf{p}}'$ of the momentum \mathbf{p}' , with $|\mathbf{p}'| = |\mathbf{p}|$.

The noise source δJ has zero time average and variance

$$\begin{aligned} \overline{\delta J(\mathbf{r}, \mathbf{p}, t) \delta J(\mathbf{r}', \mathbf{p}', t')} &= \delta(\mathbf{r} - \mathbf{r}') \delta(t - t') \delta(\varepsilon - \varepsilon') \nu^{-1} \\ &\times [4\pi \delta(\hat{\mathbf{p}} - \hat{\mathbf{p}}') \langle W(\hat{\mathbf{p}} \cdot \hat{\mathbf{p}}') (\bar{n} + \bar{n}'' - 2\bar{n}\bar{n}'') \rangle_{\hat{\mathbf{p}}''} \\ &- W(\hat{\mathbf{p}} \cdot \hat{\mathbf{p}}') (\bar{n} + \bar{n}' - 2\bar{n}\bar{n}')]. \end{aligned} \quad (4)$$

Here $\nu(\varepsilon)$ is the density of states (at energy $\varepsilon = p^2/2m^*$) and \bar{n} is the time-averaged distribution. We have set Planck's constant $\hbar \equiv 1$, so that n is dimensionless, and abbreviated $\bar{n}' = \bar{n}(\mathbf{r}, \mathbf{p}', t)$, $\bar{n}'' = \bar{n}(\mathbf{r}, \mathbf{p}'', t)$.

The force density $\mathbf{f}(\mathbf{r}, t)$ exerted by the electrons on the lattice is the divergence of a symmetric tensor $\mathbf{\Pi}$ that can be decomposed into an isotropic pressure Π_0 and a traceless shear tensor $\mathbf{\Sigma}$:

$$f_\alpha = -\nabla_\beta \Pi_{\alpha\beta}, \quad \Pi_{\alpha\beta} = \Pi_0 \delta_{\alpha\beta} + \Sigma_{\alpha\beta}. \quad (5)$$

In the approximation of a deformation-independent effective mass one has [9,11]

$$\Pi_{\alpha\beta} = m^* \int d\mathbf{p} v_\alpha v_\beta n. \quad (6)$$

The time-averaged force (5) vanishes, since it contains a derivative of the spatially uniform time-averaged distribution \bar{n} . Physically, this results from a cancellation between the electrical current drag on impurities (the so-called “wind force”) and the electric field force exerted on the ions [12]. Moreover, since \mathbf{f} is a total derivative the net fluctuating force vanishes as well at low frequencies (ignoring boundary contributions). Although the center of mass does not move, there are fluctuating compression modes (driven by Π_0) as well as torsion and bending modes (driven by $\mathbf{\Sigma}$). The driving force $\mathcal{F}(t)$ for each of these modes is obtained by weighing $\mathbf{f}(\mathbf{r}, t)$ with a sensitivity function $\mathbf{g}(\mathbf{r})$ proportional to the displacement field of the mode,

$$\mathcal{F} = \int d\mathbf{r} \mathbf{f} \cdot \mathbf{g} = \int d\mathbf{r} \left(\Pi_0 \nabla \cdot \mathbf{g} + \Sigma_{\alpha\beta} \frac{\partial g_\beta}{\partial r_\alpha} \right). \quad (7)$$

The two contributions Π_0 and $\mathbf{\Sigma}$ can be separated by expanding $n(\mathbf{r}, \mathbf{p}, t)$ in spherical harmonics $\mathbf{n}^{(q)}(\mathbf{r}, \varepsilon, t)$ with respect to the direction $\hat{\mathbf{p}}$ of the momentum. It is convenient to write the spherical harmonics in cartesian (rather than spherical) coordinates,

$$\begin{aligned} n &= \sum_{q=0}^{\infty} \overline{\hat{p}_{\alpha_1} \cdots \hat{p}_{\alpha_q}} n_{\alpha_1 \cdots \alpha_q}^{(q)} \\ &= n^{(0)} + \hat{p}_\alpha n_\alpha^{(1)} + (\hat{p}_\alpha \hat{p}_\beta - \frac{1}{3} \delta_{\alpha\beta}) n_{\alpha\beta}^{(2)} + \cdots \end{aligned} \quad (8)$$

Here $\overline{\hat{\mathbf{p}}^q}$ is the traceless part of the symmetric tensor $\hat{p}_{\alpha_1} \cdots \hat{p}_{\alpha_q}$. These tensors form an orthonormal set [13],

$$\overline{\hat{\mathbf{p}}^n \hat{\mathbf{p}}^m} = \delta_{nm} \frac{m!}{(2m+1)!!} \mathbf{\Delta}^{(m)}. \quad (9)$$

The tensor $\mathbf{\Delta}^{(m)}$ projects onto the traceless symmetric part of a tensor of rank m . We will need $\mathbf{\Delta}_{\alpha\beta}^{(1)} = \delta_{\alpha\beta}$ and

$$\mathbf{\Delta}_{\alpha\beta\alpha'\beta'}^{(2)} = \frac{1}{2} \delta_{\alpha\alpha'} \delta_{\beta\beta'} + \frac{1}{2} \delta_{\alpha\beta'} \delta_{\beta\alpha'} - \frac{1}{3} \delta_{\alpha\beta} \delta_{\alpha'\beta'}. \quad (10)$$

In view of the orthogonality of different spherical harmonics, one has

$$\Pi_0 = \frac{1}{3} \int d\varepsilon 2\varepsilon \nu n^{(0)}, \quad \Sigma_{\alpha\beta} = \frac{2}{15} \int d\varepsilon 2\varepsilon \nu n_{\alpha\beta}^{(2)}. \quad (11)$$

The two harmonics $n^{(0)}$ and $\mathbf{n}^{(2)}$ have to be found from the kinetic equation (2). We first consider the harmonic $\mathbf{n}^{(2)}$ that determines the shear tensor $\mathbf{\Sigma}$, and then discuss the harmonic $n^{(0)}$ and resulting pressure Π_0 .

To obtain an equation for $\mathbf{n}^{(2)}$ we multiply both sides of Eq. (2) by $\overline{\hat{\mathbf{p}}\hat{\mathbf{p}}}$ and perform an angular average. Employing the diffusion approximation on length and time scales larger than l and τ , we neglect the derivatives with respect to t and \mathbf{r} in Eq. (2). Also, in the linear response approximation, we neglect the derivative with respect to \mathbf{p} , since it gives a term bilinear in \mathbf{E} and \mathbf{j} . What remains is a local relation between $\mathbf{n}^{(2)}$ and the second harmonic $\mathbf{J}^{(2)}$ of the fluctuating source,

$$\mathbf{n}^{(2)} = \tau_2 \delta \mathbf{J}^{(2)}. \quad (12)$$

The momentum transport time τ_2 is defined by

$$1/\tau_2 = \frac{3}{4} \int_{-1}^1 d\xi W(\xi) (1 - \xi^2). \quad (13)$$

For anisotropic scattering the time τ_2 is larger than the charge transport time τ , defined by $1/\tau = \frac{1}{2} \int_{-1}^1 d\xi W(\xi) (1 - \xi)$. (For isotropic scattering $\tau_2 = \tau = 1/W$.)

The correlator of $\delta \mathbf{J}^{(2)}$ follows in the same way from Eq. (4). In the diffusion approximation we replace \bar{n} , \bar{n}' , \bar{n}'' by $\bar{n}^{(0)}$. Using Eq. (9) we arrive at

$$\begin{aligned} \overline{\delta \mathbf{J}_{\alpha\beta}^{(2)}(\mathbf{r}, \varepsilon, t) \delta \mathbf{J}_{\alpha'\beta'}^{(2)}(\mathbf{r}', \varepsilon', t')} &= \frac{15}{\nu \tau_2} \mathbf{\Delta}_{\alpha\beta\alpha'\beta'}^{(2)} \delta(t - t') \\ &\times \delta(\mathbf{r} - \mathbf{r}') \delta(\varepsilon - \varepsilon') \bar{n}^{(0)}(\mathbf{r}, \varepsilon) [1 - \bar{n}^{(0)}(\mathbf{r}, \varepsilon)]. \end{aligned} \quad (14)$$

Since $\bar{n}^{(0)}(\mathbf{r}, \varepsilon)$ differs from 0 or 1 only in a narrow range near the Fermi level, we ignore the energy dependence of ν and τ_2 and evaluate them at $\varepsilon = E_F$.

We quantify the transverse momentum noise through the correlator of the shear tensor,

$$C_{\alpha\beta\alpha'\beta'}^{(2)}(\mathbf{r}, \mathbf{r}') = 2 \int_{-\infty}^{\infty} dt \overline{\Sigma_{\alpha\beta}(\mathbf{r}, 0) \Sigma_{\alpha'\beta'}(\mathbf{r}', t)}. \quad (15)$$

Combining Eqs. (11), (12), and (14), we obtain the result

$$\mathcal{C}^{(2)}(\mathbf{r}, \mathbf{r}') = \frac{8}{15}(m^*v_F^2)^2\tau_2\nu\delta(\mathbf{r} - \mathbf{r}')K(\mathbf{r})\Delta^{(2)}, \quad (16)$$

$$K(\mathbf{r}) = \int d\varepsilon \bar{n}^{(0)}(\mathbf{r}, \varepsilon)[1 - \bar{n}^{(0)}(\mathbf{r}, \varepsilon)]. \quad (17)$$

The kernel K is given by [14] $K = (eV/L)x(1 - x/L)$, where V is the voltage applied between the two contacts at $x = 0, L$. The parabolic profile $K(x)$ requires $k_B T \ll eV$ and the absence of inelastic scattering.

We now turn to the pressure fluctuations. Instead of Eqs. (12) and (14) we have the fluctuating drift-diffusion equation [14]

$$\mathbf{j} + D\nabla\rho - \sigma\mathbf{E} = e\tau \int d\varepsilon \nu v \delta\mathbf{J}^{(1)} \equiv \delta\mathbf{I}, \quad (18)$$

$$\overline{\delta I_\alpha(\mathbf{r}, t)\delta I_\beta(\mathbf{r}', t')} = 2\sigma\delta_{\alpha\beta}\delta(\mathbf{r} - \mathbf{r}')\delta(t - t')K(\mathbf{r}), \quad (19)$$

which relates the fluctuations in the charge density $\rho = e \int d\varepsilon \nu n^{(0)}$ and the current density $\mathbf{j} = \frac{1}{3}e \int d\varepsilon \nu v \mathbf{n}^{(1)}$. Once we know the charge density fluctuations we can find the fluctuating pressure from

$$\Pi_0 = (D/\mu)\delta\rho, \quad (20)$$

cf. Eq. (11). We have introduced the diffusion constant $D = \frac{1}{3}v_F^2\tau$, the conductivity $\sigma = e^2\nu D$, and the mobility $\mu = e\tau/m^*$.

The correlator $\mathcal{C}^{(0)}$ of the pressure fluctuations is defined as in Eq. (15), with Σ replaced by Π_0 . To close the problem we need the continuity equation, $\partial\rho/\partial t + \nabla \cdot \mathbf{j} = 0$, and the Poisson equation $\kappa\nabla \cdot \mathbf{E} = \delta\rho$ (with κ the dielectric constant). The time derivative of ρ in the continuity equation may be omitted in the low-frequency regime of interest. The fluctuations in the electron density then obey

$$D\nabla^2\delta\rho - (\sigma/\kappa)\delta\rho = \nabla \cdot \delta\mathbf{I}. \quad (21)$$

The current fluctuations create a fluctuating charge dipole, that is screened over a length $\xi = (\kappa D/\sigma)^{1/2} = (\kappa/e^2\nu)^{1/2}$. On length scales $\gg \xi$ one may neglect the diffusion term in Eq. (21) and use the local relation [15] $\delta\rho = -(\kappa/\sigma)\nabla \cdot \delta\mathbf{I}$. Eqs. (19) and (20) then yield

$$\mathcal{C}^{(0)}(\mathbf{r}, \mathbf{r}') = \frac{4\sigma\xi^4}{\mu^2} \frac{\partial}{\partial\mathbf{r}} \cdot \frac{\partial}{\partial\mathbf{r}'} \delta(\mathbf{r} - \mathbf{r}')K(\mathbf{r}). \quad (22)$$

The next step is to use the results (16) and (22) to estimate the low-frequency noise power $\mathcal{P} = 2 \int_{-\infty}^{\infty} dt \overline{\mathcal{F}(0)\mathcal{F}(t)}$ of the fluctuating force $\mathcal{F}(t)$ that drives a particular oscillator mode. To that end the correlator (15) is integrated over \mathbf{r} and \mathbf{r}' , weighted by the sensitivity function of the mode as in Eq. (7). For a bending mode we use Eq. (16), which gives the noise power

$$\mathcal{P}^{(2)} = \frac{8}{15}(m^*v_F^2)^2\tau_2\nu \int d\mathbf{r} K(\mathbf{r})\Delta_{\alpha\beta\alpha'\beta'}^{(2)} \frac{\partial g_\beta}{\partial r_\alpha} \frac{\partial g_{\beta'}}{\partial r_{\alpha'}}. \quad (23)$$

For a compression mode in a metal of size $\gg \xi$ we use Eq. (22) and find

$$\mathcal{P}^{(0)} = \frac{4\sigma\xi^4}{\mu^2} \int d\mathbf{r} K(\mathbf{r})|\nabla\nabla \cdot \mathbf{g}|^2. \quad (24)$$

For an order of magnitude estimate, we take $K \simeq eV$, $\mathbf{g} \simeq 1$, and also estimate spatial derivatives by factors $1/L$ and the volume integral by a factor \mathcal{V} . For simplicity we assume isotropic impurity scattering, so that $\tau_2 = \tau$. Then the noise power due to fluctuations in the shear tensor is of order $\mathcal{P}^{(2)} \simeq (m^*v_F^2)^2\tau\nu eV\mathcal{V}L^{-2}$ and the noise power due to pressure fluctuations is of order $\mathcal{P}^{(0)} \simeq \sigma\xi^4\mu^{-2}eV\mathcal{V}L^{-4}$. It is instructive to write these two estimates in the same form, using the identities $\sigma/e\mu = \frac{1}{3}m^*v_F^2\nu = \mathcal{N}/\mathcal{V} \equiv n_e$, with n_e the electron density. One finds

$$\mathcal{P}^{(0)} \simeq (\xi/L)^4\mathcal{P}_{\max}, \quad \mathcal{P}^{(2)} \simeq (l/L)^2\mathcal{P}_{\max}, \quad (25)$$

with $\mathcal{P}_{\max} = \mathcal{N}m^*eV/\tau$ the noise power for independent momentum transfers mentioned in the introduction.

The experimental observation of the shear tensor fluctuations looks more promising than of the pressure fluctuations, firstly because ξ is typically $\ll (lL)^{1/2}$ so that $\mathcal{P}^{(0)} \ll \mathcal{P}^{(2)}$, and secondly because a typical oscillator operates in a bending or torsion mode rather than in a compression mode. For that reason we will now limit the more quantitative calculation to $\mathcal{P}^{(2)}$. We consider a bending mode $u(x)\cos\omega_0 t$ in the geometry of Fig. 1. The sensitivity function $g(x) = u(x)/u(x_0)$ equals the displacement (in the y -direction) normalized by the value at a reference point x_0 . We choose $x_0 = L/2$, so that \mathcal{F} is equivalent to a point force at the beam's center. Eq. (23) now takes the form

$$\mathcal{P} = \frac{4}{5}n_e p_F (l\mathcal{A}/L) \int_0^L \frac{dx}{L} K(x)[Lg'(x)]^2, \quad (26)$$

with $\mathcal{A} = \mathcal{V}/L$ the cross-sectional area of the metal layer.

The wave equation for transverse waves is biharmonic, $d^4u/dx^4 = k^4u$. The solution for doubly clamped boundary conditions is [16]

$$u(x) = (\sin kL - \sinh kL)(\cos kx - \cosh kx) - (\cos kL - \cosh kL)(\sin kx - \sinh kx), \quad (27)$$

with the resonance condition $\cos kL \cosh kL = 1$. We use the lowest resonance at $kL = 4.73$. Substituting $K = (eV/L)x(1 - x/L)$ and integrating we obtain the excess noise $\mathcal{P} = \frac{4}{5}n_e p_F (l\mathcal{A}/L) \times 0.83 eV$. If we insert values typical for a metal, $n_e = 10^{29} \text{ m}^{-3}$, $p_F = 10^{-24} \text{ Ns}$, $l = 100 \text{ nm}$, and choose typical dimensions $\mathcal{A}/L = 10 \text{ nm}$, then the force spectral density at $V = 1 \text{ mV}$ is $\mathcal{P} = 10^{-32} \text{ N}^2/\text{Hz}$. This is well above the thermal noise power at low temperatures (of order $10^{-34} \text{ N}^2/\text{Hz}$ at $T = 1 \text{ K}$ [2]).

It is instructive to apply the result (26) to a system in thermal equilibrium, when $K(x) = k_B T$ for all x . In this case an independent estimate of the noise \mathcal{P}_0 is provided by the fluctuation-dissipation theorem:

$\mathcal{P}_0 = 4k_B T M \omega_0 / Q_0$, with M the active mass of the oscillator and $1/Q_0$ the electromechanical contribution to the inverse quality factor. Eq. (26) gives

$$\frac{1}{Q_0} = \frac{1}{5} (l/L)^2 \frac{\mathcal{N} m^*}{M \omega_0 \tau} \int_0^L \frac{dx}{L} [L g'(x)]^2. \quad (28)$$

This electromechanical quality factor might be measurable in a superconducting metal, as an increase in the overall quality factor when T drops below the critical temperature. One can also calculate Q_0 directly as an “absorption of ultrasound” by conduction electrons [9], providing a consistency check on our analysis. However, the nonequilibrium noise (26) with an x -dependent kernel $K(x)$ can not be obtained from acoustic dissipation.

Before concluding we mention an altogether different mechanism for electromechanical noise, which is the coupling of a fluctuating surface charge $\delta q(t)$ on the metal to the electromagnetic environment. In the presence of an electric field E_0 between the metal surface and the substrate (*e.g.* due to a mismatch in work functions), the charge fluctuations will give rise to a fluctuating transverse force with noise power

$$\mathcal{P}_{\text{env}} \simeq E_0^2 \overline{\delta q^2} \simeq E_0^2 C^2 \overline{\delta V^2} \simeq E_0^2 C^2 R \max(k_B T, eV).$$

Here C is the capacitance to the ground and $R = L/\mathcal{A}\sigma$ the resistance of the metal. The ratio $\mathcal{P}_{\text{env}}/\mathcal{P}^{(2)} \simeq (E_0 C L^2 / e l \mathcal{N})^2$ is quite small for typical parameter values. The reason is that the environmental charge fluctuations are a surface effect, while the whole bulk of the metal contributes to $\mathcal{P}^{(2)}$. Although the noise per electron was found to be small in l/L , the total noise power $\mathcal{P}^{(2)}$ is big due to the large number $\mathcal{N} e V / E_F$ of contributing electrons.

In summary, we have addressed the fundamental question of the excitation of an elastic mode in a disordered metal out of equilibrium, as a result of the fluctuating momentum that an electrical current transfers to the lattice. The effect is small but measurable. The characteristic linear dependence of the electromechanical noise on the applied voltage should distinguish it from other sources of noise. We believe that a measurement is not only feasible but worth performing. Indeed, the nonequilibrium electric current noise has proven to be a remarkably powerful tool in the study of transport properties [17], precisely because it contains information that is not constrained by the fluctuation-dissipation theorem. The noise considered here could play a similar role for mechanical properties.

This work was motivated by discussions with M. Roukes during the Nanoscience program at the Institute for Theoretical Physics in Santa Barbara. We thank

M. Kindermann, Yu. V. Nazarov, and B. Spivak for discussions and acknowledge support by the National Science Foundation under Grant No. PHY99-07949 and No. DMR98-08941 (MRSEC program), and by the Netherlands Science Foundation NWO/FOM.

-
- [1] J. A. Sidles, J. L. Garbini, K. J. Bruland, D. Rugar, O. Züger, S. Hoen, and C. S. Yannoni, *Rev. Mod. Phys.* **67**, 249 (1995).
 - [2] M. L. Roukes, *Physics World* **14** (2), 25 (2001); *cond-mat/0008187*.
 - [3] M. M. J. Treacy, T. W. Ebbesen, and J. M. Gibson, *Nature* **381**, 678 (1996).
 - [4] B. Reulet, A. Yu. Kasumov, M. Kociak, R. Deblock, I. I. Khodos, Yu. B. Gorbatov, V. T. Volkov, C. Journet, and H. Bouchiat, *Phys. Rev. Lett.* **85**, 2829 (2000).
 - [5] H. Park, J. Park, A. K. L. Lim, E. H. Anderson, A. P. Alivisatos, and P. L. McEuen, *Nature* **407**, 57 (2000).
 - [6] M. F. Bocko, K. A. Stephenson, and R. H. Koch, *Phys. Rev. Lett.* **61**, 726 (1988); B. Yurke and G. P. Kochanski, *Phys. Rev. B* **41**, 8184 (1990); C. Presilla, R. Onofrio, and M. F. Bocko, *Phys. Rev. B* **45**, 3735 (1992); N. F. Schwabe, A. N. Cleland, M. C. Cross, and M. L. Roukes, *Phys. Rev. B* **52**, 12911 (1995).
 - [7] A. N. Cleland and M. L. Roukes, *Appl. Phys. Lett.* **69**, 2653 (1996).
 - [8] V. L. Gurevich, *Sov. Phys. JETP* **37**, 51, 1190 (1960).
 - [9] V. M. Kontorovich, *Sov. Phys. JETP* **32**, 1146 (1971); *Sov. Phys. Usp.* **27**, 134 (1984).
 - [10] Sh. M. Kogan and A. Ya. Shulman, *Sov. Phys JETP* **29**, 467 (1969); Sh. Kogan, *Electronic Noise and Fluctuations in Solids* (Cambridge University, Cambridge, 1996).
 - [11] V. B. Fiks, *Sov. Phys. JETP* **48**, 68 (1978).
 - [12] Here we ignore surface scattering. The average force is non-zero near a surface, where \bar{n} is spatially dependent. See, for example, the calculation for the case of diffuse surface scattering by M. I. Kaganov and V. B. Fiks, *Sov. Phys. JETP* **46**, 393 (1977).
 - [13] S. Hess and W. Köhler, *Formeln zur Tensor-Rechnung* (Palm & Enke, Erlangen, 1980).
 - [14] K. E. Nagaev, *Phys. Lett. A* **169**, 103 (1992).
 - [15] K. E. Nagaev, *Phys. Rev. B* **57**, 4628 (1998).
 - [16] L. D. Landau and E. M. Lifshitz, *Theory of Elasticity* (Pergamon, Oxford, 1959): §25.
 - [17] Ya. M. Blanter and M. Büttiker, *Phys. Rep.* **336**, 1 (2000).